



# **Radiation Hardness Assurance (RHA) for Space Systems**

Stephen Buchner, NASA/GSFC  
Christian Poivey, ESA

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

1

## **RHA Outline**

---

- **Introduction**
- **Programmatic aspects of RHA**
- **RHA Procedure**
  - Establish Mission requirements
  - Define and evaluate radiation hazard
  - Select parts
  - Evaluate circuit response to hazard
    - Search for data or perform a test
  - Categorize the parts
    - TID/DD
    - SEE
- **Conclusion**

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

2

## What is RHA ?

- RHA consists of all activities undertaken to ensure that the electronics and materials of a space system perform to their design specifications after exposure to the space radiation environment
- Deals with environment definition, part selection, part testing, spacecraft layout, radiation tolerant design, and mission/system/subsystems requirements

Radiation Hardness Assurance deals not only with the piece part. It includes system, subsystem, box and board levels.

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

3

## Radiation Environment in Space

### **1. Solar Wind**


- Solar Cycle
- Solar Flares
- Coronal Mass Ejections

### **2. Van Allen Belts**

- Proton Belts
- Electron Belts

### **3. Cosmic Rays**



- Galactic Origins



To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

4

# Solar Dynamic Observatory



To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

5

# Solar Dynamic Observatory

- **Contains three telescopes to study the sun**
  - Each telescope takes a picture of sun with CCD camera
  - No data processing or storage on board
  - Downlink at 150 Mbps.
  - Data storage on earth will require 250 DVDs a day
- **Geosynchronous Orbit**
  - Exposed to electron belt, solar particles (mostly protons) and galactic cosmic rays
- **Launch date is November 2008 for a 5-year Mission**
  - Spans maximum of solar activity
    - High solar wind
    - Numerous solar particle events (Coronal Mass Ejections and solar flares)
    - Reduced Galactic Cosmic Ray (GCR) flux

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

6

## Possible Radiation Effects

- **Cumulative**
  - Total Ionizing Dose (TID = 60 Mrad(Si) – free field)
  - Displacement Damage (DD = Particle Fluence)
- **Transient**
  - Non-Destructive ( $LET_{th} > 36 \text{ MeV.cm}^2/\text{mg}$ )
    - Single Event Upset (SEU),
    - Single Event Transient (SET),
    - Single Event Functional Interrupt (SEFI).
  - Destructive ( $LET_{th} > 80 \text{ MeV.cm}^2/\text{mg}$ )
    - Single Event Latchup (SEL)
    - Single Event Burnout (SEB)
    - Single Event Gate Rupture (SEGR)

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

7


## RHA Outline

- Introduction
- Programmatic aspects of RHA
- RHA Procedure
  - Establish Mission requirements
  - Define and evaluate radiation hazard
  - Select parts
  - Evaluate circuit response to hazard
    - Search for data or perform a test
  - Categorize the parts
    - TID/DD
    - SEE
- Conclusion

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

8

## Hardness Assurance (Overview)



To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

9

## RHA Outline

- Introduction
- Programmatic aspects of RHA
- **RHA Procedure**
  - Establish Mission requirements
  - Define and evaluate radiation hazard
  - Select parts
  - Evaluate circuit response to hazard
    - Search for data or perform a test
  - Categorize the parts
    - TID/DD
    - SEE
- Conclusion

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

10

# SDO Requirements

---

## **System Level Requirements.....**

1. 5-year Mission
2. Launch date is 2008
3. Must be operational 95% of the time.
4. Data integrity must be 99.99% valid.
5. Data downlink at a rate of 150 MBPS in Geosynchronous Orbit.
6. Total Mass and Mass Distribution of Spacecraft

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

11

# SDO Requirements

---

- **Flow down to Part Level Requirements**

- **Survive:**

- 5 years with total dose of 60 Mrad(Si).
    - Most failures occur near beginning, except for radiation
    - Spacecraft mass distribution determines radiation level of parts


- **SEE** rates based on budgeted down time that includes:

- Safe-hold,
    - Eclipses,
    - Instrument calibration,
    - Antenna handover,
    - Momentum shedding,
    - RADIATION

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

12

## System Hierarchy



To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

13

## Example – SDRAM Buffer

**Temporary buffer to store data from all three telescopes prior to down-linking.**

- **System Requirement**
  - Data downlink at 150 Mbps
  - 99.99% valid during 95% up time.
- **SDRAM Requirement**
  - SDRAM suffers from SEFIs due to ion strikes to control circuitry.
  - Mitigate SEFIs by rewriting registers frequently.
  - At temperatures above 42 C, SDRAM stops working.
  - Determined it was due to a timing issue
  - New mitigation involves triple-voting three SDRAMs

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

14

## RHA Challenges

---

- **Small number of systems, sometimes one, with no redundancy**
  - Requirement for high probability of survival
  - Often no qualification model
- **Electronic parts**
  - Many part types, small buys of each part type
    - No leverage with manufacturers
  - Use of Commercial Off-The-Shelf (COTS) parts
    - No configuration control
    - Obsolescence
    - Little radiation data in databases
    - Frequently only available in plastic

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

15

## RHA Outline

---

- Introduction
- Programmatic aspects of RHA
- **RHA Procedure**
  - Establish Mission requirements
  - **Define and evaluate radiation hazard**
  - Select parts
  - Evaluate circuit response to hazard
    - Search for data or perform a test
  - Categorize the parts
    - TID/DD
    - SEE
- Conclusion


To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

16



# TID Top Level Requirement (SDO)

Dose-Depth Curve for GEO




To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

17

## TID Inside Electronic Boxes

NO MARGIN

3-D Ray Trace Analysis




To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

18

## Displacement Damage Dose

200 mils = 5.08 mm

NID =  $2 \times 10^8$  MeV/gm




J. Srour (Private Communication)

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

19

## SEE - Proton Flux vs Energy

GEO




To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

20

## SEE - LET Spectra for GCRs

GEO



To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

21

## SEE Requirement

- **Destructive SEEs**

- No destructive SETs for LETs below 80 MeV·cm<sup>2</sup>/mg.
  - Mitigate (e.g., latchup protection circuit)
  - Replace part if cannot mitigate(Sometimes have no other choice but to accept part.)

- **Non-destructive SEEs**

- No non-destructive SEEs below 40 MeV·cm<sup>2</sup>/mg.
  - Mitigate if critical (e.g., majority vote)
  - Replace if cannot mitigate
  - Accept if non-critical (e.g., housekeeping)

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

22

## RHA Outline

- Introduction
- Programmatic aspects of RHA
- RHA Procedure
  - Establish Mission requirements
  - Define and evaluate radiation hazard
  - **Select parts**
  - Evaluate circuit response to hazard
    - Search for data or perform a test
  - Categorize the parts
    - TID/DD
    - SEE
- Conclusion

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007


23

## Parts Selection

Initially based on function and performance.

Additional factors are:

1. Reliability,
2. Availability,
3. Cost.



To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

24


## RHA Outline

- Introduction
- Programmatic aspects of RHA
- RHA Procedure
  - Establish Mission requirements
  - Define and evaluate radiation hazard
  - Select parts
  - Evaluate circuit response to hazard
    - Search for data or perform a test
  - Categorize the parts
- Analysis at the function/subsystem/system level
  - TID/DD
  - SEE
- Conclusion

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

25

## Search for Radiation Data




To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

26

## Sources of Radiation Data

- In house data from previous projects (LRO and SDO)
- Available databases:
  - NASA-GSFC: <http://radhome.gsfc.nasa.gov>
  - ESA: <http://escies.org>
  - DTRA ERRIC: <http://erric.dasiac.com>
- Other sources of radiation data:
  - IEEE NSREC Data Workshop, IEEE Trans. On Nuc. Sci., RADECS proceedings...
  - Vendor data

Stacked devices and hybrids  
can present a unique challenge  
for review and test



To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

27

## Evaluation of Radiation Data

Part Number	Generic Part Number	Function	Manuf.	TID/DD	Source	Destructive SEE	Source	Non-destructive SEE	Source	Notes
5962-87615012A	54AC08LM QB	Quad 2-Input AND gate	National	No radiation data		>100 MeV.cm <sup>2</sup> /mg	Manuf.	>40 MeV.cm <sup>2</sup> /mg	Manuf.	Lot specific testing needed.

↑  
Dash indicates  
not TID rad-hard

↑  
Could not  
find lot-  
specific data

↑  
Meets SDO  
requirements  
for SEL

↑  
Meets SDO  
requirements  
for SETs


↑  
Recommendation

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

28

## Evaluation of Radiation Data

Part Number	Generic Part Number	Function	Manuf.	TID/DD	Source	Destructive SEE	Source	Non-destructive SEE	Source	Notes
5962F995470 1VXC	HS-117RH	Adj. Positive Voltage Regulator	Intersil	300 krad	Manuf. Test report	>87.4 MeV.cm <sup>2</sup> /mg	Manuf. Test report	< 15 MeV.cm <sup>2</sup> /mg	Manuf. Test report	Evaluate SET threat and mitigate if necessary




To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

29

## Evaluation of Radiation Data

Item #	Part #	Function	Manuf.	TID	Source	Destructive SEEs	Non-destructive SETs	Comments	Approval
278	RMA-SLH1412D/M P-PX	DC/DC CONV, +/- 12VDC	Orbital Sciences Corporation	50 krad	?	N/A	N/A	MOSFET derated to 50% of rated BVDS to minimize risk of SEB	Accepted



To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007


30

## Radiation Test

- **Determine types of tests needed**

- TID (gamma rays),
- DD (neutrons or protons),
- SEE (protons or heavy ions).


Gamma ray  
testing with  
Co60 cell



- **Define appropriate test levels**

- Sample size,
- Particle type,
- Fluence and flux,
- Dose and dose rate.

Proton  
testing  
at UC Davis



- **Operate part as in application, i.e., bias, frequency, software, etc.**

- *Not always possible*

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

31

## Total Dose Test (Co<sup>60</sup>)

- **Dose Rate**

- Linear Bipolars: ELDRS dose rate of 0.01 rad(Si)/s
- CMOS: High dose rate of 50 to 300 rad(Si)/s

- **Total Dose**

- At least 2X of expected mission dose for part
- 100 krad(Si) better so can use data for other missions

- **Bias**

- ELDRS both biased and unbiased
- CMOS - bias to  $V_{dd}$  and  $V_{ss}$ , inputs grounded, outputs floating

- **Temperature**

- Room temperature (or application temperature), annealing step

- **Minimum Number of Parts**

- 10 with 2 for controls,
- Quad parts - must test all four.

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

32



## Single Event Test

- **Protons or Heavy Ions**
  - Determines which accelerator to use
- **Air or Vacuum**
  - For high-speed prefer air.
- **Flux**
  - Low enough to prevent "pile-up" of transients
- **Fluence**
  - Determined by statistics:
    - For SEUs minimum of 100 upsets or  $1 \times 10^7$  particles/cm<sup>2</sup>
    - For SEL minimum of  $1 \times 10^7$  particles/cm<sup>2</sup>
- **Angle**
  - Normal to grazing, depending on application
- **Temperature**
  - Room temperature for SEU, 100 C for SEL.
- **Bias**
  - $V_{dd} + 10\%$  for SEL
- **Number of parts**
  - Depends on cost of parts, availability of parts, availability of beam time (Minimum of 3)


To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

33

## SEE Test Results

- **Fit data with Weibull curve.**


$$\sigma = \sigma(\text{sat}) \cdot (1 - \exp(-(x - \text{LET}(\text{th}))/W)^S)$$
- **Extract fitting parameters:**
  - LET(th)
  - Width (W)
  - Shape (S)
  - $\sigma(\text{sat})$
- **Use fitting parameters in CREME96 or SPENVIS to calculate SEE rate.**
- **Compare calculated rate with mission requirements**



To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

34

## Radiation Test Issues - Fidelity



How accurate is the ground test in predicting space performance?  
 Example, how does aging affect dose degradation?


To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

35

## Example of Unexpected Results

- **Solid State Power Controller (SSPC) from DDC (RP-21005DO-601P)**
  - DDC replaced FET from Signetics with non rad-hard FET from IR.
  - Heavy-ion testing at Texas A&M revealed the presence of SETs causing the SSPC to switch off.
  - Pulsed laser testing revealed that the ASIC was sensitive to SETs, and that large SETs caused the SSPC to switch off.
  - Replaced DDC SSPC with Micropac SSPC
  - Previous SEE testing of ASIC at Brookhaven revealed no SETs.

Problem was range of ions at BNL



To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

36

## RHA Outline


- Introduction
- Programmatic aspects of RHA
- **RHA Procedure**
  - Establish Mission requirements
  - Define and evaluate radiation hazard
  - Select parts
  - Evaluate circuit response to hazard
    - Search for data or perform a test
  - **Categorize the parts**
    - TID/DD
    - SEE
- Conclusion

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

37

## Measurement Statistics

- **Probability of survival**
- **Confidence level**



To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

38

## Radiation Design Margin

- **Definition of RDM (for TID):**

$$\text{RDM} = \frac{\text{Mean failure level}}{\text{Maximum TID for mission}}$$

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

39

## TID Design Margin Breakpoints

$$\text{RDM} = \frac{\text{Mean failure level}}{\text{Maximum TID for mission}}$$

<b>RDM &lt; 2</b>	<b>&lt; RDM &lt; 10</b>	<b>RDM &lt; 100</b>	<b>&lt; RDM</b>
Unacceptable	Hardness Critical- HCC1	Hardness Critical- HCC2	Hardness Non-Critical
Do not use	Radiation lot testing recommended	Periodic lot testing recommended	No further action necessary

Qualitative approach recommended for systems with moderate requirements

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

40


## Part Categorization Criteria (PCC)

Log normal distribution law

$$PCC = \exp(K_{TL} s)$$

$K_{TL}$  = One sided tolerance factor based on sample size  $n$ ,  
confidence level  $C$  and probability of survival  $P_s$

$s$  = standard deviation of sample data



After MIL HDBK-814


To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

41

## Parts Categorization Criteria

$P_s=0.999$   
 $C=0.9$   
 $N=30$  samples  
Gives  
 $K=3.79$


$PCC = \exp(3.79 \cdot 0.365)$   
 $= 3.99$



To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

42

## TID- Example of Application



To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

43


## TID Mitigation

- **Reduce the dose levels**
  - Improve the accuracy of the dose level calculation
  - Change the electronic board, electronic box layout
  - Add shielding
    - Different location on spacecraft
    - Box shielding
    - Spot shielding
- **Increase the failure level**
  - Test in the application conditions
  - Test at low dose rate (CMOS only)
  - Tolerant designs (cold redundancies, etc.)
  - Relax the functional requirements

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

44

## TID Mitigation – Spot Shielding



To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

45

## TID Mitigation - Examples

- **TMS320C25 (DSP) Texas Instruments – LEO polar**

- TID soft: 3 krad(Si) (functional failure)
- Duty cycle in the application: 10% on
- TID tolerance with application duty cycle: 10 krad

The device has operated flawlessly during the mission

- **FPGA 1280 ACTEL - GEO**

- TID soft: 3 krad functional at high dose rate.
- TID at 1 rad/h: ~ 14 krad functional, 50 mA power consumption increase (max design value) after 8 krad.
- Spot shielding with Ta: received dose = 4 krad

EADS-Astrium data

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

46

## RHA Outline


- Introduction
- Programmatic aspects of RHA
- RHA Procedure
  - Establish Mission requirements
  - Define and evaluate radiation hazard
  - Select parts
  - Evaluate circuit response to hazard
    - Search for data or perform a test
  - **Categorize the parts**
    - TID/DD
    - SEE
- Conclusion

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

47

## SEE - Analysis Requirements

- $LET_{th} > 80$ 
  - SEE risk **negligible**, no further analysis needed
- $80 > LET_{th} > 15$ 
  - SEE risk **moderate**, heavy-ion induced SEE rates must be analyzed. In many cases SEEs can be tolerated. Requires analysis.
- $15 > LET_{th}$ 
  - SEE risk **high**, heavy ion and proton induced SEE rates to be analyzed. In many cases can tolerate the SEEs




To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

48




## SEE - Analysis Flow



To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

49

## SEE - Decision Tree



To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

50

## RHA Outline

---

- Introduction
- Programmatic aspects of RHA
- RHA Procedure
  - Establish Mission requirements
  - Define and evaluate radiation hazard
  - Select parts
  - Evaluate circuit response to hazard
    - Search for data or perform a test
  - Categorize the parts
    - TID/DD
    - SEE
- Conclusion

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

51

## Conclusion

---

- The RHA approach is based on risk management and not on risk avoidance
- The RHA process is not confined to the part level, but includes
  - Spacecraft layout
  - System/subsystem/circuit design
  - System requirements and system operations
- RHA should be taken into account in the early phases of a program, including the proposal and feasibility analysis phases.

To be presented by S. Buchner at SERESSA in Buenos Aires, December 10-12, 2007

52